

MODERN STATISTICS BY KRIGING

T. SUSŁO

ABSTRACT. We present statistics (S-statistics) based only on random variable (not random value) with a mean squared error of mean estimation as a concept of error.

1. ORIGIN

Remark. Notation

$$\omega_j^i \rho_{ij}$$

is equivalent to

$$\sum_{i=1}^n \omega_j^i \rho_{ij} = \omega' \rho ,$$

where

$$\omega = \omega_j^i = \underbrace{\begin{bmatrix} \omega_j^1 \\ \vdots \\ \omega_j^n \end{bmatrix}}_{n \times 1}, \quad \rho = \rho_{ij} = \underbrace{\begin{bmatrix} \rho_{1j} \\ \vdots \\ \rho_{nj} \end{bmatrix}}_{n \times 1}.$$

Notation

$$\omega_j^i \rho_{ii} \omega_j^i$$

is equivalent to

$$\sum_{i=1}^n \sum_{l=1}^n \omega_j^i \omega_j^l \rho_{il} = \sum_{i=1}^n \omega_j^i \sum_{l=1}^n \rho_{il} \omega_j^l = \omega' \Lambda \omega ,$$

where

$$\rho_{il} = \Lambda = \Lambda' = \rho_{ii} = \underbrace{\begin{bmatrix} \rho_{11} & \cdots & \rho_{1n} \\ \vdots & \ddots & \vdots \\ \rho_{n1} & \cdots & \rho_{nn} \end{bmatrix}}_{n \times n}.$$

Let us consider (e.g. for $j = n + 1$) variance of the difference R_j of two random variables V_j and $\hat{V}_j$, where $E\{V_j\} = E\{\hat{V}_j\} = m$, in terms of covariance

$$\begin{aligned} D^2\{V_j - \hat{V}_j\} &= Cov\{(V_j - \hat{V}_j)(V_j - \hat{V}_j)\} \\ &= Cov\{V_j V_j\} - Cov\{V_j \hat{V}_j\} - Cov\{\hat{V}_j V_j\} + Cov\{\hat{V}_j \hat{V}_j\} \\ &= Cov\{V_j V_j\} - 2Cov\{V_j \hat{V}_j\} + Cov\{\hat{V}_j \hat{V}_j\} \end{aligned}$$

introducing the estimation statistics $\hat{V}_j = \sum_i \omega_j^i V_i = \omega_j^i V_i$

$$\begin{aligned}
D^2\{R_j\} &= Cov\{V_j V_j\} - 2Cov\{\hat{V}_j V_j\} + Cov\{\hat{V}_j \hat{V}_j\} \\
&= Var\{V_j\} - 2Cov\{\sum_i \omega_j^i V_i V_j\} + Cov\{(\sum_i \omega_j^i V_i)(\sum_i \omega_j^i V_i)\} \\
&= \sigma^2 - 2\sum_i \omega_j^i Cov\{V_i V_j\} + \sum_i \sum_l \omega_j^i \omega_j^l Cov\{V_i V_l\} \\
&= \sigma^2 - 2\sigma^2|\omega_j^i \rho_{ij}| + \sigma^2|\omega_j^i \rho_{ii} \omega_j^i| \\
&= \sigma^2 \pm 2\sigma^2 \omega_j^i \rho_{ij} \mp \sigma^2 \omega_j^i \rho_{ii} \omega_j^i
\end{aligned}$$

in terms of correlation function ρ

$$D^2\{R_j\} = \sigma^2 + 2\sigma^2 \omega_j^i \rho_{ij} - \sigma^2 \omega_j^i \rho_{ii} \omega_j^i$$

if

$$\omega_j^i \rho_{ij} < 0$$

and

$$\omega_j^i \rho_{ii} \omega_j^i < 0$$

or

$$D^2\{R_j\} = \sigma^2 - 2\sigma^2 \omega_j^i \rho_{ij} + \sigma^2 \omega_j^i \rho_{ii} \omega_j^i$$

if

$$\omega_j^i \rho_{ij} \geq 0$$

and

$$\omega_j^i \rho_{ii} \omega_j^i \geq 0 .$$

The unbiasedness constraint (I condition)

$$E\{R_j\} = E\{V_j - \hat{V}_j\} = E\{V_j\} - E\{\hat{V}_j\} = 0$$

is equivalent to

$$\sum_i \omega_j^i = 1 .$$

The minimization constraint

$$\frac{\partial D^2\{R_j\}}{\partial \omega_j^i} = 0 ,$$

where

$$D^2\{R_j\} = \sigma^2 \pm 2\sigma^2 \omega_j^i \rho_{ij} \mp \sigma^2 \omega_j^i \rho_{ii} \omega_j^i \mp 2\sigma^2 \underbrace{\left(\sum_i \omega_j^i - 1\right)}_0 \mu_j ,$$

produces n equations in the $n + 1$ unknowns: kriging weights ω_j^i and a Lagrange parameter μ_j (II condition)

$$\underbrace{\begin{bmatrix} \rho_{11} & \dots & \rho_{1n} & 1 \\ \vdots & \ddots & \vdots & \vdots \\ \rho_{n1} & \dots & \rho_{nn} & 1 \end{bmatrix}}_{n \times (n+1)} \cdot \underbrace{\begin{bmatrix} \omega_j^1 \\ \vdots \\ \omega_j^n \\ \mu_j \end{bmatrix}}_{(n+1) \times 1} = \underbrace{\begin{bmatrix} \rho_{1j} \\ \vdots \\ \rho_{nj} \end{bmatrix}}_{n \times 1}$$

multiplied by ω_j^i

$$\omega_j^i \rho_{ii} \omega_j^i + \underbrace{\mu_j \sum_i \omega_j^i}_1 = \omega_j^i \rho_{ij}$$

and substituted into $D^2\{R_j\}$

$$\begin{aligned}
D^2\{R_j\} &= E\{[V_j - \hat{V}_j]^2\} - \underbrace{E\{V_j - \hat{V}_j\}}_0 \\
&= E\{[(V_j - m) - (\hat{V}_j - m)]^2\} \\
&= E\{[V_j - m]^2\} - 2(E\{V_j \hat{V}_j\} - m^2) + E\{[\hat{V}_j - m]^2\} \\
&= \sigma^2 - 2\sigma^2|\omega_j^i \rho_{ij}| + \sigma^2|\omega_j^i \rho_{ii} \omega_j^i| \\
&= \sigma^2 \pm 2\sigma^2 \omega_j^i \rho_{ij} \mp \sigma^2 \omega_j^i \rho_{ii} \omega_j^i
\end{aligned}$$

give the minimized variance of the field V_j under estimation

$$E\{[(V_j - m) - (\hat{V}_j - m)]^2\} = \sigma^2(1 \pm (\omega_j^i \rho_{ij} + \mu_j))$$

and these two conditions produce $n + 1$ equations in the $n + 1$ unknowns

$$\underbrace{\begin{bmatrix} \rho_{11} & \dots & \rho_{1n} & 1 \\ \vdots & \ddots & \vdots & \vdots \\ \rho_{n1} & \dots & \rho_{nn} & 1 \\ 1 & \dots & 1 & 0 \end{bmatrix}}_{(n+1) \times (n+1)} \cdot \underbrace{\begin{bmatrix} \omega_j^1 \\ \vdots \\ \omega_j^n \\ \mu_j \end{bmatrix}}_{(n+1) \times 1} = \underbrace{\begin{bmatrix} \rho_{1j} \\ \vdots \\ \rho_{nj} \\ 1 \end{bmatrix}}_{(n+1) \times 1}.$$

2. ASYMPTOTIC PROPERTIES OF ORIGIN

Since

$$\lim_{n \rightarrow \infty} D^2 \left\{ \sum_{i=1}^n \omega_j^i V_i \right\} = 0$$

then

$$\lim_{n \rightarrow \infty} \omega_j^i V_i = \lim_{n \rightarrow \infty} \omega_j^i v_i$$

and (since)

$$\lim_{n \rightarrow \infty} E \left\{ \sum_{i=1}^n \omega_j^i V_i \right\} = m$$

then

$$\lim_{n \rightarrow \infty} E \left\{ \sum_{i=1}^n \omega_j^i V_i \right\} = \lim_{n \rightarrow \infty} \sum_{i=1}^n \omega_j^i v_i = m$$

the minimized variance of the field V_j under estimation

$$E\{[(V_j - m) - (\hat{V}_j - m)]^2\} = \sigma^2(1 \pm (\omega_j^i \rho_{ij} + \mu_j))$$

has known asymptotic property

$$\lim_{n \rightarrow \infty} E\{[V_j - \hat{V}_j]^2\} = \lim_{n \rightarrow \infty} E\{[V_j - \omega_j^i v_i]^2\} = E\{[V_j - m]^2\} = \sigma^2.$$

3. THE FIELD UNDER ESTIMATION

Let us consider the field V_j under estimation

$$\hat{V}_j = \omega_j^i V_i,$$

where for auto-estimation holds

$$\hat{V}_i = \delta_i^i V_i = V_i,$$

with minimized variance of the estimation statistics

$$\begin{aligned}
E\{[\hat{V}_j - m]^2\} &= Cov\{(\omega_j^i V_i)(\omega_j^i V_i)\} \\
&= \sum_i \sum_l \omega_j^i \omega_j^l Cov\{V_i V_l\} \\
&= \sigma^2 |\omega_j^i \rho_{ii} \omega_j^i| \\
&= \mp \sigma^2 (\omega_j^i \rho_{ij} - \mu_j),
\end{aligned}$$

where for auto-estimation holds

$$E\{[\hat{V}_i - m]^2\} = E\{[V_i - m]^2\} = \sigma^2$$

that means outcoming of input value is unknown for mathematical model, with minimized variance of the field V_j under estimation

$$E\{[(V_j - m) - (\hat{V}_j - m)]^2\} = \sigma^2 (1 \pm (\omega_j^i \rho_{ij} + \mu_j))$$

where for auto-estimation holds

$$E\{[(V_i - m) - (\hat{V}_i - m)]^2\} = \underbrace{E\{[V_i - m]^2\}}_{\sigma^2} - \underbrace{2(E\{V_i \hat{V}_i\} - m^2)}_{2\sigma^2} + \underbrace{E\{[\hat{V}_i - m]^2\}}_{\sigma^2} = 0$$

that means variance of the field is equal to variance of the (auto-)estimation statistics (not that auto-estimation matches observation).

4. GENERALIZED LEAST SQUARES SOLUTION

For $j \rightarrow \infty$

$$\underbrace{\begin{bmatrix} \rho_{1j} \\ \vdots \\ \rho_{nj} \end{bmatrix}}_{n \times 1} = \xi \underbrace{\begin{bmatrix} 1 \\ \vdots \\ 1 \end{bmatrix}}_{n \times 1} \quad \xi \rightarrow 0^- \text{ (or } \xi \rightarrow 0^+)$$

and a disjunction of the minimized variance of the field V_j under estimation

$$E\{[V_j - m]^2\} - \underbrace{(E\{V_j \hat{V}_j\} - m^2)}_{\mp \sigma^2 \xi} + \underbrace{E\{\hat{V}_j [\hat{V}_j - V_j]\}}_{\mp \sigma^2 \xi} \quad \text{if } \rho_{ij} \omega_j^i + \mu_j = \xi + \mu_j = 0$$

which fulfills its asymptotic property the kriging system

$$\underbrace{\begin{bmatrix} \rho_{11} & \cdots & \rho_{1n} & 1 \\ \vdots & \ddots & \vdots & \vdots \\ \rho_{n1} & \cdots & \rho_{nn} & 1 \\ 1 & \cdots & 1 & 0 \end{bmatrix}}_{(n+1) \times (n+1)} \cdot \underbrace{\begin{bmatrix} \omega^1 \\ \vdots \\ \omega^n \\ -\xi \end{bmatrix}}_{(n+1) \times 1} = \underbrace{\begin{bmatrix} \xi \\ \vdots \\ \xi \\ 1 \end{bmatrix}}_{(n+1) \times 1}$$

equivalent to

$$\Lambda \omega - \xi F = \xi F$$

and

$$F' \omega = 1$$

where: $F = (1, \dots, 1)'$, $\omega = (\omega^1, \dots, \omega^n)'$, $\Lambda = \Lambda' = \rho_{ii}$; $i = 1, \dots, n$, has the least squares solution

$$\xi = \frac{1}{2F' \Lambda^{-1} F}$$

and

$$\omega = 2\xi \Lambda^{-1} F = \frac{\Lambda^{-1} F}{F' \Lambda^{-1} F}$$

with a mean squared error of mean estimation

$$E\{[\hat{V}_j - m]^2\} = \mp \sigma^2 2\xi .$$

5. APPROACH TO SIMPLE STATISTICS (CONCLUSION)

For white noise

$$\begin{aligned} E\{[(V_j - m) - (\hat{V}_j - m)]^2\} &= E\{[V_j - m]^2\} + E\{[\hat{V}_j - m]^2\} \\ &= \sigma^2(1 - \mu_j) \\ &= \sigma^2 \left(1 + \frac{1}{n}\right) \end{aligned}$$

since

$$\lim_{n \rightarrow \infty} E\{[\hat{V}_j - m]^2\} = 0$$

then

$$\lim_{n \rightarrow \infty} \hat{V}_j = m$$

and

$$\lim_{n \rightarrow \infty} E\{[(V_j - m) - (\hat{V}_j - m)]^2\} = \sigma^2 .$$

Remark. Precession of arithmetic mean can not be identical to 0 cause a straight line fitted to high-noised data by ordinary least squares estimator can not have the slope identical to 0. For this reason the estimator of an unknown constant variance

$$\frac{1}{n} \text{ sum of deviation squares}$$

in fact is the lower bound for precession of the minimized variance of the field under estimation

$$E\{[(V_j - m) - (\hat{V}_j - m)]^2\} = \sigma^2 \left(1 + \frac{1}{n}\right)$$

to increase ‘a bit’ the lower bound for $n \rightarrow \infty$ we can effect on weight and reduce total counts n by 1 because 1 is the closest positive integer number to 0 so it is easy to find the closest weight such that

$$\frac{1}{n-1} > \frac{1}{n-0}$$

then the so-called unbiased variance

$$\frac{1}{n-1} \text{ sum of deviation squares}$$

in fact is the simplest estimator of minimized variance of the field under estimation.

REFERENCES

- [1] E. H. Isaaks and R. M. Srivastava, *An Introduction to Applied Geostatistics*, New York: Oxford Univ. Press (1989) 279–307.
- [2] <http://www.compsoc.man.ac.uk/~lucky/Democritus/Theory/corfun1.html>